

610-1000T





PART NUMBERS

610 - 1000T

1000 Turns

OUTLINE DRAWING



The **610-1000T** Split Core Current Transformer is designed for assembly to an existing electrical installation without the need for dismantling the primary bus or cables. It incorporates a snap fit between the fixed and removable sections.

This transformer is intended for use with high input impedance devices that require signal voltages up to 5 VAC.

The output can be rectified and filtered for devices requiring DC input. The non-linearity and voltage drop of the rectifiers and filters must be considered in the choice of the loading impedance.

Application

For Energy Management Systems and Instrumentation
Equipment having a High Input Impedance, eg. 14K ohms minimum

Frequency

50-400 Hz

Insulation Level

0.6 kV, BIL 10 kV full wave

Construction

The core and windings are encased in UL approved plastic

Continuous Thermal Current Rating

Factor 330A at 30° C amb

250A at 55° C amb

Flexible Leads

UL 1015 105° C, CSA approved, #18 AWG, 24" long unless otherwise specified

Approximate Weight

10 oz

Regulatory Agencies

